

## EOL9-1612-19X Series

Single-Mode 1.25G 1470~1610nm

Duplex 1 x 9 Transceiver

RoHS6 Compliant



### Features

- ◆ Duplex SC/FC/ST Single-Mode Transceiver
- ◆ Industry Standard 1 x 9 Footprint
- ◆ CWDM DFB-LD Transmitter
- ◆ 3.3V or 5V single power supply
- ◆ PECL signal input and output <sup>\*note1</sup>
- ◆ Signal detect indicator (PECL version) <sup>\*note1</sup>
- ◆ Wave Solderable and Aqueous Washable  
with process plug inserted
- ◆ Class 1 FDA and IEC60825-1 laser safety  
compliant
- ◆ 19dB power budget
- ◆ Operating Case Temperature  
Standard: 0°C~+70°C

### Applications

- ◆ Gigabit Ethernet
- ◆ Fiber channel
- ◆ Switch to Switch Interface
- ◆ Digital video transmission system

### Ordering information

Part No.	Input	Output	SD	Power Budget	Voltage	Interface	Temp.
EOL9-1612-19X <sup>*note2</sup> X <sup>*note3</sup>	AC	DC	PECL	19dB	3.3V/5V	SC	Standard
EOL9-1612-19X <sup>*note2</sup> TX <sup>*note3</sup>	AC	DC	PECL	19dB	3.3V/5V	ST	Standard
EOL9-1612-19X <sup>*note2</sup> FX <sup>*note3</sup>	AC	DC	PECL	19dB	3.3V/5V	FC	Standard

Note1: 5V for PECL or TTL, 3.3V for LVPECL or LVTTTL

Note2: Standard version, X refers to CWDM center wavelength, from K to R means 1470nm to 1610nm.

Note3: Standard version, X means AC/DC coupling, SD PECL, SC connector. Please contact EOPTOLINK to confirm whether other options are available,

## CWDM\* Wavelength from 1470nm to 1610nm

Band	Nomenclature	Wavelength(nm)		
		Min.	Typ.	Max.
S-band Short Wavelength	K	1464	1470	1477.5
	L	1484	1490	1497.5
	M	1504	1510	1517.5
	N	1524	1530	1537.5
C-band Conventional	O	1544	1550	1557.5
L-band Long Wavelength	P	1564	1570	1577.5
	Q	1584	1590	1597.5
	R	1604	1610	1617.5

CWDM\*: 8 Wavelengths from 1470nm to 1610nm, each step 20nm.

## Regulatory Compliance

Feature	Standard	Performance
Electrostatic Discharge (ESD) to the Electrical Pins	MIL-STD-883G Method 3015.7	Class 1C (>1000 V)
Electrostatic Discharge to the enclosure	EN 55024:1998+A1+A2 IEC-61000-4-2 GR-1089-CORE	Compliant with standards
Electromagnetic Interference (EMI)	FCC Part 15 Class B EN55022:2006 CISPR 22B :2006 VCCI Class B	Compliant with standards Noise frequency range: 30 MHz to 6 GHz. Good system EMI design practice required to achieve Class B margins. System margins are dependent on customer host board and chassis design.
Immunity	EN 55024:1998+A1+A2 IEC 61000-4-3	Compliant with standards. 1kHz sine-wave, 80% AM, from 80 MHz to 1 GHz. No effect on transmitter/receiver performance is detectable between these limits.
Laser Eye Safety	FDA 21CFR 1040.10 and 1040.11 EN (IEC) 60825-1:2007 EN (IEC) 60825-2:2004+A1	CDRH compliant and Class I laser product. TüV Certificate No. 50135086


Component Recognition	UL and CUL EN60950-1:2006	UL file E317337 TüV Certificate No. 50135086 (CB scheme )
RoHS6	2002/95/EC 4.1&4.2 2005/747/EC 5&7&13	Compliant with standards <sup>*note4</sup>

Note4: For update of the equipments and strict control of raw materials, EOPTOLINK has the ability to supply the customized products since Jan 1st, 2007, which meet the requirements of RoHS6 (Restrictions on use of certain Hazardous Substances) of European Union.

In light of item 5 in RoHS exemption list of RoHS Directive 2002/95/EC, Item 5: Lead in glass of cathode ray tubes, electronic components and fluorescent tubes.

In light of item 13 in RoHS exemption list of RoHS Directive 2005/747/EC, Item 13: Lead and cadmium in optical and filter glass. The three exemptions are being concerned for Eoptolink's transceivers, because Eoptolink's transceivers use glass, which may contain Pb, for optical components such as lenses, isolators, and other electronic components.

## Functional Diagram



The Signal Detect (SD, active high), Normal optical input of receiver represents to a logic "1" level, which means asserted.

## Product Description

The EOL9-1612-19X Series Single-mode transceivers are low power, high performance modules for duplex optical data communications such as Gigabit Ethernet and Fiber Channel.

The transmitter section uses a multiple quantum well WDM DFB laser and is a class1 laser compliant according to International Safety Standard IEC-60825. The receiver section uses an integrated InGaAs detector preamplifier (IDP) mounted in an optical header and a limiting post-amplifier IC.

A PECL logic interface simplifies interface to the external circuitry.

## Absolute Maximum Ratings\*

Parameter	Symbol	Min.	Max.	Unit	
Storage Temperature	$T_S$	-40	+85	°C	
Supply Voltage	$V_{CC}$	5V	-0.5	7.0	V
		3.3V	-0.5	5.5	
Operating Relative Humidity	-		95	%	
Soldering Conditions Temp/Time			260/10	°C/s	

\*Exceeding any one of these values may destroy the device immediately.

## Recommended Operating Conditions

Parameter	Symbol	Min.	Typical	Max.	Unit
Operating Case Temperature	$T_C$	0		+70	°C
Power Supply Voltage	$V_{CC}$	4.75	5	5.25	V
		3.15	3.3	3.45	
Power Supply Current <sup>*(note5)</sup>	$I_{CC}$			300	mA
Data Rate			1.25		Gbps

Note5: Maximum current is specified at Vcc equaling to Maximum @ maximum temperature.

## Optical and Electrical Characteristic

Parameter	Symbol	Min.	Typical	Max.	Unit
Data Rate			1.25		Gbps
Power Budget		19			dB
<b>Transmitter</b>					
Centre Wavelength	$\lambda_C$	$\lambda_C - 6$	$\lambda_C$	$\lambda_C + 7.5$	nm
Spectral Width(-20dBm)	$\Delta\lambda$			1	nm
Average Output Power <sup>*(note6)</sup>	$P_{out}$	-5		0	dBm
Extinction Ratio	ER	9			dB
Rise/Fall Time (20%---80%)	tr/tf			260	ps
Relative Intensity Noise	RIN			-117	dB/Hz
Total Jitter	TJ			56.5	ps
Data Input Swing Differential	$V_{in}$	400		2000	mV
Input Differential Impedance	$Z_{in}$	90	100	110	$\Omega$
Input High Voltage	$V_H$	-1165		-880	mV
Input Low Voltage	$V_L$	-1810		-1475	mV
Eye Diagram	Compliant with IEEE 802.3ah-2004 <sup>*(note8)</sup>				
Data Input	PECL <sup>*(note1)</sup>				
<b>Receiver</b>					
Input center wavelength	$\lambda_C$	1260		1620	nm
Receiver Sensitivity <sup>*(note7)</sup>	$P_{min}$			-24	dBm
Receiver Overload	$P_{max}$	-3			dBm



SD Assert	SDA			-25	dBm
SD De-Assert	SDD	-40			dBm
SD Hysteresis <sup>*(note9)</sup>		0.5			dB
Output High Voltage	V <sub>H</sub>	-1165		-880	mV
Output Low Voltage	V <sub>L</sub>	-1810		-1475	mV
SD Voltage(PECL-H) <sup>*(note1)</sup>	V <sub>H</sub>	-1.1		-0.74	V
SD Voltage (PECL-L) <sup>*(note1)</sup>	V <sub>L</sub>	-2.0		-1.58	V
Data Output	PECL <sup>*(note1)</sup>				

Note6: The optical power is launched into 9/125um SMF.

Note7: Minimum average optical power measured at BER less than 1E-12, with a 2<sup>7</sup>-1 PRBS and ER=9 dB.

Note8: Eye pattern mask


Note9: LOS Hysteresis(SD signal coincides with the LOS signal inversion)




## Pin Description

Pin	Name	Level	Description
1	Veer		Receiver Signal Ground, connect to receiver signal ground plane directly
2	RD+	PECL <sup>*(note1)</sup>	Receiver data out
3	RD-	PECL <sup>*(note1)</sup>	Inverted receiver data out
4	SD	PECL <sup>*(note1)</sup>	Signal Detect, PECL output, Normal optical input levels to the receiver result in a logic "1" output, asserted. Low input levels to the receiver result in a fault condition indicated by a logic "0" output, de-asserted.
5	Vccr		Receiver Power Supply, provide +5V (+3.3V) the recommended receiver power supply filter circuit. Locate the power filter circuit as close as possible to the Vccr pin
6	Vcct		Transmitter Power Supply, provide +5V DC(+3.3V) via the recommended transmitter power supply filter circuit. Locate the power filter circuit as close as possible to the Vcct pin
7	TD-	PECL <sup>*(note1)</sup>	Inverted transmitter Data in
8	TD+	PECL <sup>*(note1)</sup>	Transmitter Data in
9	Veet		Transmitter Signal Ground, connect to the transmitter signal ground plane directly

Pin Definitions




Recommended Circuit




R2/R6: 100 Ω  
 R3/R4: 150 Ω  
 C1/C2/C3/C4/C7/C8: 0.1uF  
 C5/C6/C9: 10uF  
 L1/L2: 1uH

R8/R12/R10/R14: Depends on SerDes chips used  
 R7/R11/R9/R13: Depends on SerDes chips used


Package outline (Unit: mm)



SC receptacle



FC receptacle




ST receptacle

### Laser Emission Data

Wavelength	>1460nm
Total output power (as defined by FDA: 7 mm aperture at 20 cm distance)	<0.79mW
Total output power (as defined by IEC: 7 mm aperture at 10 cm distance)	<10mW
Beam divergence	12.5°

### Laser Emission



### Obtaining Document

You can visit our website:

<http://www.eoptolink.com>

Or contact Eoptolink Technology Inc., Ltd. Listed at the end of the documentation to get the latest documentation.

## Revision History

Revision	Initiated	Reviewed	Approved	DCN	Release Date
V1.a	Torres, Xavi, Angela	Kelly	Alex	Released.	Feb 25, 2013

### Notice:

Eoptolink reserves the right to make changes or discontinue any product or service identified in this publication, without notice, in order to improve design and/or performance. Applications that are described herein for any of the products are for illustrative purposes only. Eoptolink makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

### Contact:

Add: Floor 5 Building 2 No. 21 Gaopeng Avenue High-Tech District CHENGDU, SICHUAN 610041

P.R. CHINA

Tel: (+86) 028-85124308 ext 801

Fax: (+86) 028-85121912

Postal: 610041

E-mail:sales@eoptolink.com

<http://www.eoptolink.com>